



# RT112

## 10.1 Inch Android Rugged Tablet

5G & WLAN 6E | Longevity QCM5430 Processor | IP67 & 1.5M Drop



### Powered by Android 13 OS with GMS & AER Certified

The RT112 is a 10.1-inch Android 13 rugged tablet equipped with an advanced 64-bit Hexa Cores CPU capable of reaching speeds up to 2.1 GHz. It effortlessly handles demanding tasks while ensuring smooth multitasking. With the distinction of Google Certification, encompassing Google Mobile Service (GMS) and Android Enterprise Recommended (AER) endorsement, the dual certification assures a secure and efficient business environment.

### Seamless and Connectivity via Wireless Communication

Featuring Bluetooth® 5.2, wireless WLAN 6E with fast roaming and 5G connectivity for real-time data collection, user can scan the item and instantly connect to the backend system to find out the quantity in stock or make an online order for customers. The RT112 delivers a seamlessly work experience and improves productivity for various applications, making it faster downloads and uploads at user's fingertips on the most reliable networks for your business.

### 5G IOT Platform

Equipped with the Qualcomm 5430 5G IoT Platform, the RT112 offers seamless integration into the future of technology. Its robust 5G capabilities ensure lightning-fast data transfer and a responsive online experience, all while being optimized for the demands of the Internet of Things. With a focus on longevity, the RT112 boasts an extended life cycle, making it an ideal investment for those seeking a device that will remain relevant and efficient for years to come.

### Durable Design

The RT112 enhances the industrial durable protection with features including IP67 dustproof, waterproof, and 1.5 meters resistance to fall protection. That means it covers fully protected from dust and can survive in 1 meter of water for up to 30 mins. The MIL-STD-810H standard assures an overall environmental vibration and humidity. The light tablet with a slim 12mm edge is designed for workers to comfortably capture data and check inventory in high portability from day to night. For an easy touch and view, the 10.1" display supports glove and wet touch mode with 450 nits.

### Features

- Android 13 with GMS & AER Certified
- 10.1" (1920 x 1200) LCD display with Gorilla® Glass (450 nits)
- Lightweight but durable: 690g with 12mm
- Rugged Design: IP67 rated, 1.5M drop and MIL-STD-810H certified
- Wireless Communication: 5G & WLAN 6E
- 5G IOT Platform (Qualcomm 5430): Support Long Life Cycle

### System Features

|               |  |
|---------------|--|
| OS            | Android 13.0 with AER certified  |
| GMS certified | GMS certified  |
| CPU           | Qualcomm Snapdragon™ 5430 Processor, 64bits, Hexa Cores up to 2.1 GHz (Option: Octa Cores) |
| Memory        | 6GB RAM + 128GB Flash<br>(Option: 8GB RAM + 128GB Flash)                                   |
| AI            | 6th Gen Qualcomm AI Engine   |
| Others        | Qualcomm® Trusted Execution Environment (TEE)  |

### Display

10.1" (1920 x 1200) LCD Display 450 nits  
Gorilla® Glass, Multi-Touch User Interface with Capacitive, stylus, glove, wet-finger Compatibility

### Buttons / Keypad

6 Physical Buttons  
Power, Volume+/-, Scan Key x 2, Programable Key x 1

### Indicator

LEDs, Vibrator

### RFID

Support HF/NFC  
ISO14443-4 (Type A, Type B), ISO15693, Mifare, Felica(ISO/IEC18092)

### I/O Interfaces

|                |  |
|----------------|--|
| USB            | USB3.1 Type-C x 1  |
| POGO PIN       | POGO pin   |
| SIM Slot       | Nano SIM x 1   |
| Expansion Slot | Micro SD Card x 1  |
| Audio          | Dual-speakers<br>MIC*2<br>(noise cancelling & Background noise depression) |

### Power Source

Main Battery 8800mAh (removable)

### Software

Support MDM Software Solutions and utilities such as Airwatch, SOTI, Ivanti Wavelink, and MoboLink

### Regulatory Approvals

CE, UKCA, FCC, IC, NCC, BSMI, VCCI, TELEC, CCC, SRRC, BQB, RoHS, REACH

### Symbologies

|        |  |
|--------|--|
| 1D     | Codabar, Code 11, Code 128, Code 2 of 5, Code 39, Code 93 and 93i, EAN/JAN-13, EAN/JAN 8, IATA Code 2 of 5, Interleaved 2 of 5, Matrix 2 of 5, MSI, GS1 Databar, UPC-A, UPC E, UPC-A/EAN-13 with Extended Coupon Code, Coupon GS1 Code 32 (PARAF), EAN-UCC Emulation, GS1 Data Bar |
| 2D     | Codablock A, Codablock F, PDF417, MicroPDF417, Aztec Code, Data Matrix, MaxiCode, QR Code, Chinese Sensible (Han Xin), Grid Matrix, Dot Code   |
| Postal | Australian Post, British Post, Canadian Post, China Post, Japanese Post, Korea Post, Netherlands Post, Planet Code, Postnet  |

### Communication

|                 |   |
|-----------------|---|
| Camera          | Rear:13M (with auto-focus and LED flash, Support Google Arcore & Depth API)<br>Front:5M (with fixed focus)  |
| Bluetooth®      | Bluetooth® 5.2  |
| WLAN            | WLAN 6E, 2.4GHz & 5GHz & 6GHz<br>Support Dual-Band Simultaneous (DBS)<br>IEEE 802.11a/b/g/n/ac/d/h/i/k/r/v/ac/ax (2x2 MU-MIMO)  |
| WWAN (Optional) | 5G FR1 Sub 6GHz:<br>N1/N2/N3/N5/N28/N41/N48/N66/N71/N77/N78/N79 (4x4 MIMO)<br>4G LTE (FDD) – Bands 1, 2, 3, 4, 5, 7, 8, 12, 13, 17, 20, 28, 66, 71<br>LTE (TDD) – Bands 38, 39, 40, 41<br>3G UMTS/HSPA+ – Bands 1, 2, 5, 8<br>2G GSM/GPRS/EDGE (850/900/1800/1900 MHz)<br>Support 2G/3G/4G/5G |
| GPS             | GPS, BeiDou, Glonass, Galileo, QZSS, NavIC and SBAS (for WWAN model only)   |
| Sensors         | Gyroscope, Accelerometer (G-sensor), E-compass, Light & Proximity Sensor  |

### Enclosure

|            |              |
|------------|--------------|
| Dimensions | 260x165x12mm |
| Weight     | 690g         |

### Environment

|                          |  |
|--------------------------|--|
| Operating temperature    | -20°C ~ 55°C                             |
| Storage temperature      | -40°C ~ 70°C                             |
| Drop test to Concrete    | 1.5m                                     |
| Environmental Sealing    | IP67                                     |
| Vibration and Shock test | MIL-STD-810H, Method 516.8, Procedure IV |

### What comes in the box

RT112  
Battery Pack  
USB-C Adaptor

### Accessories

Rotatable Hand Strap  
Shoulder Strap  
Screen Protector  
Office Cradle  
Vehicle Cradle  
Capacitive Stylus Pen (5.5mm) w/ Coil Strap



### Headquarters

Taipei, Taiwan  
<http://www.ute.com> e-mail: [info@hq.ute.com](mailto:info@hq.ute.com)

### unitech America

Los Angeles  
<http://us.ute.com> e-mail: [info@us.ute.com](mailto:info@us.ute.com)  
<http://can.ute.com> [info@can.ute.com](mailto:info@can.ute.com)  
Mexico  
<http://latin.ute.com> e-mail: [info@latin.ute.com](mailto:info@latin.ute.com)

### unitech Asia Pacific & Middle East

Taipei  
<http://apac.ute.com> [info@apac.ute.com](mailto:info@apac.ute.com) / [info@india.ute.com](mailto:info@india.ute.com)  
<http://mideast.ute.com> [info@mideast.ute.com](mailto:info@mideast.ute.com)

### unitech Europe

Tilburg / Netherlands  
<http://eu.ute.com> e-mail: [info@eu.ute.com](mailto:info@eu.ute.com)

### unitech Japan

Tokyo  
<http://jp.ute.com> e-mail: [info@jp.ute.com](mailto:info@jp.ute.com)

### unitech Greater China

Beijing, Shanghai, Guang Zhou, Xiamen  
<http://cn.ute.com> [info@cn.ute.com](mailto:info@cn.ute.com)  
Taipei <http://tw.ute.com> [info@tw.ute.com](mailto:info@tw.ute.com)



### Development Tools



Unitech SDK



Scanner SDK



RFID SDK

Unitech offers a number of SDK toolkits for developers to write apps that can interact with the unitech devices for the mobile, scanner, and the RFID product lines.

### Device Management



### Staging and Management



MoboLink

Android Enterprise ready EMM for monitoring device health and managing apps, configs and files.



StageGO

Barcode-based device staging utility offering hundreds of script commands for you to work with.



OEMConfig

If you are using a third party EMM, OEMConfig will allow those EMM solutions to configure unitech specific settings on the device.



Enterprise Launcher

Secure your devices by kiosk them with Enterprise Launcher. Block access to the Android system and only allow limited number of apps to be run.



Battery info

Monitor advanced Battery health and manage the battery replacement cycle. Use with MoboLink to get real-time battery health alerts delivered to your phone.



Software Update

Check and install software updates online. To let a device always stay up-to-date, setup the device to automatically check and install for updates on boot up.



System Update Center

Check and install firmware updates via FOTA. You can update the firmware via online FOTA server, or by using a OTA ZIP file placed in the internal storage.



Unitech Scanner Utility

An Android application which helps users connect, configure and use a supported Unitech Bluetooth scanner.

### Productivity and Utilities




USS

Configure all scanner settings with friendly user interface and enable the service to make scanning data as keypad input.



USS Profiles



USS Camera

Capture barcode data using the device camera and send the data to your applications as keyboard inputs.



KeyRemap

Reprogram physical buttons to act as another key or to launch an app.



WLAN Advanced

Configure advanced WLAN settings such as power saving mode and roaming parameters.



NTP Server Settings

Customize the NTP server setting to keep your device date and time synchronized.



UNote

A simple text viewer and editor for use in your work flows.



Startup

Auto-run apps when device boots up.



TagAccess

For versatile functions of RFID command via integrating with Unitech RFID Readers.



Logger

An easy and fast way to get logs from a device.



Enterprise Keyboard

Enterprise Keyboard gives various methods for user to input data to enhance efficiency and productivity.